

# PRODUCT DATA SHEET

## CARECALL4 COORDINATOR

### SM-PDS-00121 v1.00



## PRODUCT INFO

### SCALABLE

CareCall4 Coordinators are available in 16, 48, and 96 port varieties – making it perfectly suited to provision medium to high volumes of field devices.

### REDUNDANCY OPERATION

Devices connected to Coordinators remain operational in the event of server communications loss. Ports feature thermally resetting fuse, protecting other devices and enabling rapid fault resolution.



**CareCall4 Coordinators** collect structured cabling from field devices allowing them to intercommunicate and providing them uplink to CareCall EDGE Alarm Server across a nominated LAN for supervision, reporting, and wider alarm distribution.

Each 2 x 2 bay of ports is protected with thermally resetting fuses, preventing interruptions to other devices if line faults arise. CareCall Addressable Over-Door Lights will present a fault indication pattern where the fuses for adjacent ports have been detected as tripped.

## FRONT PANEL INTERFACES

CareCall Net Interfaces	1 x 16 (16), 3 x 16 (48), 6 x 16 (96)
LED	Power indicator

## REAR PANEL INTERFACES

LAN	RJ45
Power	2-position screw terminal
Serial RS232	DB9 female
Serial RS485	5-position screw terminal
CareCall3 Bus	4-position screw terminal

## POWER

Voltage	12V
Current	10A (max)

# PRODUCT DATA SHEET

CARECALL4 COORDINATOR  
SM-PDS-00121 v1.00



## SIZE

<b>Rack</b>	2RU, 19 inches
<b>Dimensions</b>	86(H) x 482(W) x 225(D)
<b>Package Dimensions</b>	95(H) x 540(W) x 450(D)
<b>Weight</b>	2.9 (96), 2.3 (48), 2.1 (16) Kg

## ENVIRONMENTAL & MATERIALS

<b>Material</b>	Aluminium
<b>Operating Temperature</b>	0 - 70°C
<b>Storage Temperature</b>	-25 - +85°C

## COMPATIBILITY

<b>CareCall Nurse Call</b>	CareCall4, CareCall3
<b>CareCall4 Config Tool</b>	v1.01g (minimum recommended)
<b>CareCall EDGE</b>	v4.08d (minimum recommended)

## ORDERING

<b>Coordinator 96</b>	C4-COORDINATOR-96
<b>Coordinator 48</b>	C4-COORDINATOR-48
<b>Coordinator 16</b>	C4-COORDINATOR-16
<b>Licensing</b>	SOF-20433 (first 3 Coordinators), SOF-20434 (fourth and beyond)

